



# 17 & 20kW<sup>†</sup> STANDBY GENERATORS

## POWER YOU CAN DEPEND ON

Help your customers protect their homes and families from power outages with Milbank's new and improved 17-20kW<sup>†</sup> home generator systems. Perfect for medium-to-large homes, we provide you with reliable power and flexible options to meet your customers' power needs.



### AVAILABLE ACCESSORIES

**Basic Wireless Monitor | Model MG622901**  
(sold separately)



Easy, trouble-free monitoring is a reality with the new Milbank Basic Wireless Monitor. Place the wireless monitor in your home and know your generator is working without ever having to go outside.

**Note:** Installations must strictly comply with all applicable codes, industry standards, laws and regulations. Running engines give off carbon monoxide, an odorless, colorless, poison gas so it is important to keep exhaust gas away from any windows, doors, ventilation intakes or crawl spaces. Carbon monoxide detectors must be installed and maintained in your home.

**Note:** Milbank reserves the right to make changes in specifications and features shown without notice or discontinue the product described at any time without notice or obligation.



# 17 & 20KW STANDBY GENERATORS

## PERMANENT PROTECTION FROM A PROVEN PERFORMER

**Flexible Placement** – Tested against tough National Fire Protection Agency standards, Milbank 17kW' and 20kW' standby generators can be placed as close as 18" from the home providing more placement options in your yard - perfect for tight lot lines.

**Reliable Engine Power** – Our standby generators are powered by commercial-grade Vanguard™ engines that are design-engineered to dependably take on the most demanding jobs.

**Power Solution Options** – Choose between an Essential Power-Plus! system that powers a select number of circuits plus 2 air conditioners or a Managed Whole House Power system that powers all of your household appliances plus up to 2 air conditioners with our Load Control Center.

**Durable Enclosure** – Rust-resistant, Galvanneal steel enclosures are made from the same materials and paint process used in the automotive industry, resulting in years of protection against chips and abrasions.

**Quick Response** – Automatically powers your home in seconds after sensing a power outage.

**4-Year Limited Parts and Labor Warranty** – At Milbank, we stand behind our warranty and make it easy for our customers to work with us.

## SPECIFICATIONS

<b>Model Number</b>	MG17001	MG20003
<b>Watts (LP)</b>	17,000	20,000
<b>Watts (NG)</b>	15,300	18,000
<b>Frequency</b>	60 Hz	60 Hz
<b>Fuel Type</b>	Propane (LP Vapor), Natural Gas (NG)	Propane (LP Vapor), Natural Gas (NG)
<b>Operation</b>	Fully Automatic	Fully Automatic
<b>Voltage</b>	120/240V AC, Single Phase, 1.0 pf	120/240V AC, Single Phase, 1.0 pf
<b>Amps LP/NG</b>	67.0/60.0	83.3/75.0
<b>Alternator</b>	Brushed, Computer Friendly	Brushed, Computer Friendly
<b>Voltage Regulation</b>	Automatic	Automatic
<b>Engine</b>	993cc Briggs & Stratton Vanguard™ V-Twin	993cc Briggs & Stratton Vanguard™ V-Twin
<b>Full Pressure Lubrication</b>	Yes	Yes
<b>Overcrank Protection</b>	Yes	Yes
<b>Dimensions (L x W x H)</b>	48" x 34" x 31"	48" x 34" x 31"
<b>Weight (generator only)</b>	484 lbs.	500 lbs.
<b>Limited Warranty*</b>	4 Year Parts and Labor	4 Year Parts and Labor
<b>Turn-Key Extras Included</b>	Battery Charger, Hour Meter, Installation Base	Battery Charger, Hour Meter, Installation Base

† These generators are rated in accordance with UL 2200 and CSA Standard C22.2 No. 100-04  
 ‡ Fuel consumption rates are estimated based on normal operating conditions. Generator operation may be greatly affected by elevation and the cycling operation of multiple electrical appliances – fuel flow rates may vary depending on these factors.



**4 YEAR WARRANTY**

